# AC-DC Switching Power Supply GK220S -25W Series

# **HenLv**

### **Features**

- Wide voltage input: 90-264VAC/127-370VDC
- Metal mesh shell packaging, good heat dissipation
- Isolation voltage:3000VAC5mA1Minute
- Operating temperature range:-40°C∼+85°C
- Comply with international and domestic safety regulations
- International standard pin
- Heat dissipation mode: natural air cooling
- High efficiency, long life and high reliability
- Protection function: short circuit, over load, over voltage and over temperature

# **Product Picture**











EMC-EN55032 EN55035 LVD-EN62368

### **Dimensions**

#### **GK220S\_-25W Series Dimensions**



	Front View	5,00 [0	,197]	<del> -</del> ,
299]	□			-
33,00 [1,299]	00	0	00	3,50 [0,138] 7,75 [0,305]



Pin mode			
Pin Function			
1	AC(L)		
2	AC(N)		
3	FG		
4	-V		
5	+V		

Note:

Size unit: mm[inch]

Wiring diameter: 22-14AWG

Connector torque size: M3,  $0.4N \cdot m$ Unmarked tolerance:  $\pm 1.00[\pm 0.039]$ The device layout is for reference only.



HenLv Technology (NingBo) Co., Ltd

# **AC-DC** Switching Power Supply

GK220S -25W Series



### **Application**

Industrial control and remote DC power supply systems, switching systems :AC/DC(5V products). Railway communication, communication interface conversion cellular telephone, semiconductor laser, display screen, Monitoring equipment, petrochemical, portable instrument, medical instrument, automatic control device, burglar alarm, handheld instrument, digital circuit, IC card meter, air conditioning computer controller, LED products, digital products, power adapter, etc.

Selection Guide						
Model	Input(V)	Output (Vo±2%)	Current (mA)	Efficiency (%)	Adjustable output voltage Range ADJ (V)	Isolation (VAC)
GK220S05-25W		5	5000	75	4.75-5.5	3000
GK220S12-25W	90-264VAC (127-370VDC)	12	2083	79	10.8-13.2	3000
GK220S15-25W		15	1666	79	13.5-16.5	3000
GK220S24-25W		24	1041	80	22-27.6	3000
GK220S48-25W		48	520	80	43.2-52.8	3000

Note: Our company can customize the module power supply with any input and output for customers. If you have special needs, please call our company. Unless otherwise specified, the input = Vi. The characteristics of the module power supply should comply with the provisions of Table 1 and be applicable to the full temperature range (-40°C≤Tc≤85°C)

Electrical Specifications					
Specifications Symbol		Conditions Vi ,-40°C≤Tc≤85 (Unless otherwise specified)	Min	Max	Unit
Output Voltage	Vo	Full Load	Vo-2%	Vo+2%	V
Output Current	Iomax	_	_	P(Power)/ U(Output voltage)	Α
Output Ripple Voltage	Vp-p	Full Load,Vi,BW=20MHz,Normal Temperature	80	200	mV
Output Noise Voltage	Vp-p	Full Load, Vi, BW=20MHz, Normal Temperature	80	200	mV
Voltage Regulation	Sv	Vimin、Vi、Vimax,Full Load	_	≤±2%	%
Load Adjustment	Si	Vi,lo=(10%~100%)lomax	_	≤±2%	%
Insulation Resistance	Rl	Input/Output, Test Voltage: 500VDC	100	_	МΩ

General Specifications				
	Magnetic Field Sensitivity Test	GB6833.2-87		
	Electrostatic Discharge Sensitivity Test GB6833.2-87			
EMC Specifications	Radiation Sensitivity Test	GB6833.2-87		
	<b>Conduction Sensitivity Test</b>	GB6833.2-87		
Temperature Drift	≤±0.02%/°C			
Storage Temperature	-40°C~85°C			
Input Frequency	47Hz~63Hz			
Humidity	10%~95%RH			
Leakage Current	<2mA/240VDC			
MTBF	>500000H			




# AC-DC Switching Power Supply GK220S -25W Series




## **Mechanical Specifications**

Size 84.00 x 58.00 x 33.00 mm

### Typical SpecificationsCurves




## Output Power/Input Voltage Curve



### **Precautions**

### **Package**

This series of modules are packed in shockproof and anti-static foam.



### **Transport**

The package containing the module is allowed to be transported by any means of transport, which should avoid direct rain and snow and mechanical damage.

### Storage

The module should be stored in a warehouse where the ambient temperature is -40 degrees ~ 125 degrees, the relative humidity is 20%~95%, and the surrounding environment is free from acidic, alkaline and other harmful gases.

Note: The above are the performance indicators of the product series listed in this manual. Some indicators of non-standard products may exceed the above requirements, so if there is any inconsistency between the manual and the product specification documents, please refer to the specification documents. If you have special needs, please contact us directly.

